

Adjust R1

The Adjust R1 gives you full manual control over your Fractal Design Prisma AL Series fans and other standard 5V addressable RGB devices. A single Adjust R1 provides easy software-free control, customization, and synchronized effects for several fans, LED strips, and other ARGB devices in daisy-chain or Y-cable configurations.

Intuitive controls let you set customize colors, configure brightness, and set color cycling modes with a variety of pulse and motion effects.





Key features

- Simple and intuitive controls
- Compatible with standard 5V ARGB LED fans, strips, and devices
- Integrated magnets for convenient placement in any steel case
- Preset color, color cycle, custom color, long rainbow, and short rainbow modes
- Eight color presets and five brightness levels
- Six pulse and motion effects
- Remembers settings when powered off
- Included Y-cable and adapters

Package contents

- Adjust R1 RGB Controller
- RGB Y-cable (female-to-female)
- 2 x Male-to-male adapters



Specification

Compatibility	 5V Addressable RGB devices with standard 3-pin connector
Color modes	Preset color: Set all LEDs to red, green, blue, orange, cyan, yellow, purple, or white
	Color cycle: All LEDs change color in unison
	 Custom color: Freeze color cycle mode on the exact color of your choice
	Long rainbow: Colors animate in a long sequence
	Short rainbow: Colors animate in a quick succession
Brightness settings	• 5 levels
Pulse and motion effects	On (constant brightness)
	Slow breathing effect
	Fast breathing effect
	Slow single pulse sequence
	Fast single pulse sequence
	Slow marquee chasing effect
	Fast marquee chasing effect
	Off (LEDs disabled)
Maximum load	• 2.6A
Product dimensions	• 45 x 17 x 8 mm
Product weight	• 14 g
Package dimensions	• 134 x 134 x 33 mm
Package weight	• 70 g



Additional information

Product SKU EAN UPC JAN

Adjust R1 FD-ACC-ADJ-R1-BK 7340172701576 843276101572 4537694262743